



**User Manual** 

## **Contact Information**

If you need to contact ASRock or want to know more about ASRock, you're welcome to visit ASRock's website at http://www.asrock.com; or you may contact your dealer for further information. For technical questions, please submit a support request form at https://event.asrock.com/tsd.asp

## **ASRock Incorporation**

e-mail: info@asrock.com.tw

ASRock EUROPE B.V.

e-mail: sales@asrock.nl

ASRock America, Inc.

e-mail: sales@asrockamerica.com



Scan the QR code to view more manuals and documents.

# Contents

Chap	oter 1 Introduction	1
1.1	Package Contents	1
1.2	Specifications	2
1.3	Motherboard Layout	7
1.4	I/O Panel	9
1.5	Block Diagram	11
1.6	802.11be Wi-Fi 7 Module and ASRock WiFi 2.4/5/6 GHz Antennas	12
Chap	oter 2 Installation	14
2.1	Installing the CPU	15
2.2	Installing the CPU Fan and Heatsink	18
2.3	Installing Memory Modules (DIMM)	27
2.4	Connecting the Front Panel Header	29
2.5	Installing the Motherboard	30
2.6	Installing SATA Drives	31
2.7	Installing a Graphics Card	33
2.8	Connecting Peripheral Devices	35
2.9	Connecting the Power Connectors	36
2.10	Power On	37
2.11	Jumpers Setup	38
2.12	Onboard Headers and Connectors	39
2.13	Smart Button	52

2.14	Post Status Checker	54
2.15	M.2 SSD Installation Guide (M2_1)	55
2.16	M.2 SSD Installation Guide (M2_2)	58
2.17	M.2 SSD Installation Guide (M2_3)	61
2.18	M.2 SSD Installation Guide (M2_4)	64

# **Chapter 1 Introduction**

Thank you for purchasing ASRock X870 LiveMixer WiFi motherboard, a reliable motherboard produced under ASRock's consistently stringent quality control. It delivers excellent performance with robust design conforming to ASRock's commitment to quality and endurance.



Because the motherboard specifications and the BIOS software might be updated, the content of this documentation will be subject to change without notice. In case any modifications of this documentation occur, the updated version will be available on ASRock's website without further notice. If you require technical support related to this motherboard, please visit our website for specific information about the model you are using. You may find the latest VGA cards and CPU support list on ASRock's website as well. ASRock website <a href="http://www.asrock.com">http://www.asrock.com</a>.

## 1.1 Package Contents

- · ASRock X870 LiveMixer WiFi Motherboard (ATX Form Factor)
- 2 x Serial ATA (SATA) Data Cables (Optional)
- 2 x ASRock WiFi 2.4/5/6 GHz Antennas (Optional)
- 1 x Thermistor Cable (Optional)

## 1.2 Specifications

## **Platform**

- · ATX Form Factor
- · 8 Layer PCB

## **CPU**

- Supports AMD Socket AM5 Ryzen<sup>TM</sup> 9000, 8000 and 7000 Series Processors\*
- \* The availability of expansion slots may vary by CPU. Please refer to PCIe/M.2 Bandwidth Table for details. (http://www.asrock.com/)

## Chipset

· AMD X870

#### Memory

- · Dual Channel DDR5 Memory Technology
- · 4 x DDR5 DIMM Slots
- Supports DDR5 ECC/non-ECC, un-buffered memory up to 8000+(OC)\*
- · Max. capacity of system memory: 256GB
- Supports Extreme Memory Profile (XMP) and EXTended Profiles for Overclocking (EXPO) memory modules
- \* Please refer to Memory Support List on ASRock's website for more information. (http://www.asrock.com/)

# Expansion Slot

#### CPU:

- 1 x PCIe 5.0 x16 Slot (PCIE1), supports x16 mode\* Chipset:
- 2 x PCIe 3.0 x16 Slots (PCIE2 and PCIE3), support x4 mode\*
- 1 x M.2 Socket (Key E), supports type 2230 WiFi/BT PCIe WiFi module
- \* PCIE1 will run at Gen5x16 with 9000 and 7000 series processors, Gen4x8 with 8000 (Phoenix 1) series processors and Gen4x4 with 8000 (Phoenix 2) series processors.
- \* If M2\_3 is occupied, PCIE2 will downgrade to x2 mode.
- \* If M2\_4 is occupied, PCIE3 will downgrade to x2 mode.
- \* Supports NVMe SSD as boot disks
- 15µ Gold Contact in VGA PCIe Slot (PCIE1)

## Graphics

- Integrated AMD RDNA<sup>TM</sup> graphics (Actual support may vary by CPU)
- 1 x HDMI 2.1 TMDS/FRL 8G Compatible, supports HDR, HDCP 2.3 and max. resolution up to 4K 120Hz
- 2 x USB4, support HDCP 2.3 and max. resolution up to 8K 30Hz\*
- \* Only the CPU's embedded graphics can be displayed through USB4 ports. If you want to display to a Type-C monitor, please use AM5 Ryzen<sup>TM</sup> 9000, 8000 and 7000 processors with embedded graphics.
- \* USB4 controller(for USB4\_TC1 and USB4\_TC2) will run at Gen4x2 with with 8000 (Phoenix 2) series processors.

#### **Audio**

- 7.1 CH HD Audio with Content Protection (Realtek ALC4082 Audio Codec)
- · Individual PCB Layers for R/L Audio Channel
- · Nahimic Audio

#### LAN

- · 5 Gigabit LAN 10/100/1000/2500/5000 Mb/s
- · Realtek RTL8126

## Wireless LAN

- 802.11be 2x2 Wi-Fi 7 Module
- Supports IEEE 802.11a/b/g/n/ac/ax/be
- · Supports 2.4GHz/5GHz/6GHz\* frequency band
- Supports 160MHz channel bandwidth with 6GHz\* frequency band
- \* The Wi-Fi 7 module is supported by Microsoft\* Windows\* 11 only. There is no driver available for Windows\* 10. The availability of the 6GHz band will depend on the different regulation status of each country and region. It will be activated (for supported countries) through Windows\* Update and software updates once available.
- 1 antenna to support 2 (Transmit) x 2 (Receive) diversity technology
- Supports Bluetooth 5.4
- · Supports MU-MIMO

#### **USB**

#### CPU:

- 2 x USB4 Type-C (Rear)
- 2 x USB 3.2 Gen1 Type-A (Rear (USB32\_1 and USB32\_4)) Chipset:
- 1 x USB 3.2 Gen2x2 Type-C (Front)
- 9 x USB 3.2 Gen1 Type-A (5 Rear (USB32\_2, USB32\_356, USB32\_7), 4 Front))
- 1 x USB 3.2 Gen1 Type-C (Rear)
- 10 x USB 2.0 (6 Rear, 4 Front)
- \* All USB ports support ESD Protection

## Rear Panel I/O

- 2 x Antenna Ports
- · 1 x HDMI Port
- 1 x Optical SPDIF Out Port
- 2 x USB4 Type-C Ports (40 Gb/s)\*
- 1 x USB 3.2 Gen1 Type-C Port
- 7 x USB 3.2 Gen1 Type-A Ports (USB32\_34 are Lightning Gaming Ports. USB32\_56 support Ultra USB Power.)
- 6 x USB 2.0 Ports
- · 1 x RJ-45 LAN Port
- · 1 x BIOS Flashback Button
- 1 x Line Out Jack (Gold Audio Jack)
- 1 x Microphone Input Jack (Gold Audio Jack)
- \* Supports USB PD 3.0 up to 5V@3A (15W) charging
- \* USB4 controller(for USB4\_TC1 and USB4\_TC2) will run at Gen4x2 with with 8000 (Phoenix 2) series processors.
- \* If M2\_2 is occupied, both rear USB4 Type-C Ports and M2\_2 will downgrade to x2 mode. You can switch M2\_2 to x4 mode in BIOS setting, but doing so will disable USB4\_TC1 and USB4\_TC2.

#### Storage

#### CPU:

- 1 x Blazing M.2 Socket (M2\_1, Key M), supports type 2280 PCIe Gen5x4 (128 Gb/s) mode\*
- 1 x Blazing M.2 Socket (M2\_2, Key M), supports type 2280 PCIe Gen5x4 (128 Gb/s) mode\*

#### Chipset:

- 1 x Hyper M.2 Socket (M2\_3, Key M), supports type 2280 PCIe Gen4x4 (64 Gb/s) mode\*
- 1 x Hyper M.2 Socket (M2\_4, Key M), supports type
   2230/2242/2260/2280 PCIe Gen4x4 (64 Gb/s) mode\*
- 2 x SATA3 6.0 Gb/s Connectors
- \* Supports NVMe SSD as boot disks
- \* M2\_1 is the first priority for M.2 installation.
- \* M2\_1 will run at Gen5x4 with 9000 and 7000 series processors and Gen4x4 with 8000 (Phoenix 1 and Phoenix 2) series processors.
- \* M2\_2 will run at Gen5x4 with 9000 and 7000 series processors and Gen4x4 with 8000 (Phoenix 1) series processors. M2\_2 will be unavailable with 8000 (Phoenix 2) series processors.
- \* If M2\_2 is occupied, both rear USB4 Type-C Ports and M2\_2 will downgrade to x2 mode. You can switch M2\_2 to x4 mode in BIOS setting, but doing so will disable USB4\_TC1 and USB4\_TC2.
- \* If M2\_3 is occupied, PCIE2 will downgrade to x2 mode.
- \* If M2\_4 is occupied, PCIE3 will downgrade to x2 mode.

#### **RAID**

- Supports RAID 0 and RAID 1 for SATA storage devices
- Supports RAID 0, RAID 1 and RAID 10 for M.2 NVMe storage devices

### Connector

- · 1 x SPI TPM Header
- · 1 x Thermistor Cable Header
- · 1 x Power LED and Speaker Header
- · 1 x RGB LED Header\*
- · 3 x Addressable LED Headers\*\*
- 2 x CPU Fan Connectors (4-pin) (Smart Fan Speed Control)\*\*\*
- 3 x Chassis Fan Connectors (4-pin) (Smart Fan Speed Control)\*\*\*
- 1 x AIO Pump Fan Connector (4-pin) (Smart Fan Speed Control)\*\*\*
- 1 x 24 pin ATX Power Connector (Hi-Density Power Connector)

- 2 x 8 pin 12V Power Connectors (Hi-Density Power Connector)
- · 1 x Front Panel Audio Connector
- 2 x USB 2.0 Headers (Support 4 USB 2.0 ports)
- 2 x USB 3.2 Gen1 Headers (Support 4 USB 3.2 Gen1 ports)
- 1 x Front Panel Type C USB 3.2 Gen2x2 Header (20 Gb/s)
- \* Supports in total up to 12V/3A, 36W LED Strip
- \*\* Support in total up to 5V/3A, 15W LED Strip
- \*\*\* CPU\_FAN1 supports the fan power up to 1A (12W).
- \*\*\* CPU\_FAN2, CHA\_FAN1~3 and AIO\_PUMP support the fan power up to 3A (36W).
- \*\*\* CPU\_FAN2, CHA\_FAN1~3 and AIO\_PUMP can auto detect if 3-pin or 4-pin fan is in use.

RIO2	
Feature	

· AMI UEFI Legal BIOS with GUI support

OS

· Microsoft® Windows® 10 64-bit / 11 64-bit

Certifica-

· FCC, CE

tions


• ErP/EuP ready (ErP/EuP ready power supply is required)

<sup>\*</sup> For detailed product information, please visit our website: http://www.asrock.com



Please realize that there is a certain risk involved with overclocking, including adjusting the setting in the BIOS, applying Untied Overclocking Technology, or using third-party overclocking tools. Overclocking may affect your system's stability, or even cause damage to the components and devices of your system. It should be done at your own risk and expense. We are not responsible for possible damage caused by overclocking.


## 1.3 Motherboard Layout



Νo	D	es	cri	рt	ioı	

- 1 ATX 12V Power Connector (ATX12V1)
- 2 ATX 12V Power Connector (ATX12V2)
- 3 2 x 288-pin DDR5 DIMM Slots (DDR5\_A1, DDR5\_B1)
- 4 CPU Fan Connector (CPU\_FAN1)
- 5 CPU Fan Connector (CPU FAN2)
- 6 AIO Pump Fan Connector (AIO\_PUMP)
- 7 2 x 288-pin DDR5 DIMM Slots (DDR5\_A2, DDR5\_B2)
- 8 Post Status Checker (PSC)
- 9 Addressable LED Header (ADDR LED3)
- 10 Addressable LED Header (ADDR\_LED2)
- 11 ATX Power Connector (ATXPWR1)
- 12 USB 3.2 Gen1 Header (USB32\_10\_11)
- 13 Front Panel Type C USB 3.2 Gen2x2 Header (USB32\_TC2)
- 14 SPI TPM Header (SPI\_TPM\_J1)
- 15 USB 3.2 Gen1 Header (USB32\_8\_9)
- 16 SATA3 Connector (SATA3\_1)
- 17 SATA3 Connector (SATA3 2)
- 18 System Panel Header (PANEL1)
- 19 Power LED and Speaker Header (SPK\_PLED1)
- 20 USB 2.0 Header (USB\_9\_10)
- 21 USB 2.0 Header (USB\_7\_8)
- 22 Clear CMOS Jumper (CLRCMOS1)
- 23 Chassis Fan Connector (CHA\_FAN1)
- 24 Chassis Fan Connector (CHA\_FAN2)
- 25 Addressable LED Header (ADDR\_LED1)
- 26 RGB LED Header (RGB\_LED1)
- 27 Thermistor Cable Header (T\_SENSOR1)
- 28 Front Panel Audio Header (HD AUDIO1)
- 29 Chassis Fan Connector (CHA\_FAN3)

## 1.4 I/O Panel



No	Description	No	Description
1	Antenna Ports	9	USB 3.2 Gen1 Type-A Port (USB32_7)
2	USB 3.2 Gen1 Type-A Ports	10	USB 3.2 Gen1 Type-C Port (USB32_TC1)
	(USB32_56)*	11	USB4 Type-C Port (USB4_TC2)****
3	USB 2.0 Ports (USB_123)	12	USB4 Type-C Port (USB4_TC1)****
4	USB 2.0 Ports (USB_456)	13	USB 3.2 Gen1 Type-A Ports
5	5G LAN RJ-45 Port**		(USB32_34)****
6	Microphone Input Jack***	14	USB 3.2 Gen1 Type-A Ports (USB32_12)
7	Line Out Jack***	15	BIOS Flashback Button
8	Optical SPDIF Out Port	16	HDMI Port

<sup>\*</sup>USB32\_56 support Ultra USB Power.

## ACT/LINK LED



LAN Port

Activity / Link LED		Speed LED	Speed LED		
Status	Description	Status	Description		
Off	No Link	Off	10Mbps connection		
Blinking	Data Activity	Orange	100Mbps/1Gbps/2.5		
			connection		
On	Link	Green	5Gbps connection		
			connection		

<sup>\*\*</sup> There are two LEDs on each LAN port. Please refer to the table below for the LAN port LED indications.


\*\*\* Function of the Audio Ports in 2, 4, 5.1 or 7.1-channel Configuration:

Channel	Port	Function	
2ch	Line Out Jack	Enont on colton out	
2011	(Rear Panel)	Front speaker out	
4ch	Pink-Mic	Rear speaker out	
4011	(Front Panel)	Real speaker out	
5.1ch	Microphone Input Jack	Central/Subwoofer speaker out	
J.1CII	(Rear Panel)	Central/Subwooler speaker out	
7.1ch	Lime-Headphone	C: do Carolton out	
7.1011	(Front Panel)	Side Speaker out	

<sup>\*\*\*\*</sup> USB4 controller(for USB4\_TC1 and USB4\_TC2) will run at Gen4x2 with with 8000 (Phoenix 2) series processors.

<sup>\*\*\*\*\*</sup>  $USB32\_34$  are the Lightning Gaming Ports.

## 1.5 Block Diagram



# 1.6 802.11be Wi-Fi 7 Module and ASRock WiFi 2.4/5/6 GHz Antennas

#### 802.11be Wi-Fi 7 + BT Module

This motherboard comes with an exclusive 802.11 a/b/g/n/ac/ax/be Wi-Fi 7 + BT v5.4 module that offers support for 802.11 a/b/g/n/ac/ax/be Wi-Fi 7 connectivity standards and Bluetooth v5.4. Wi-Fi 7 + BT module is an easy-to-use wireless local area network (WLAN) adapter to support Wi-Fi 7 + BT. Bluetooth v5.4 standard features Smart Ready technology that adds a whole new class of functionality into the mobile devices.


- \* The transmission speed may vary according to the environment.
- \* The Wi-Fi 7 module is supported by Microsoft\* Windows\* 11 only. There is no driver available for Windows\* 10. The availability of the 6GHz band will depend on the different regulation status of each country and region. It will be activated (for supported countries) through Windows\* Update and software updates once available.

## WiFi Antennas Installation Guide




#### Step 1

Prepare the WiFi 2.4/5/6 GHz Antennas that come with the package.



#### Step 2

Connect the two WiFi 2.4/5/6 GHz Antennas to the antenna connectors. Turn the antenna clockwise until it is securely connected.



## Step 3

Set the WiFi 2.4/5/6 GHz Antenna as shown in the illustration.

\*You may need to adjust the direction of the antenna for a stronger signal.

# **Chapter 2 Installation**

This is an ATX form factor motherboard. Before you install the motherboard, study the configuration of your chassis to ensure that the motherboard fits into it.

## **Pre-installation Precautions**

Take note of the following precautions before you install motherboard components or change any motherboard settings.

- Make sure to unplug the power cord before installing or removing the motherboard components. Failure to do so may cause physical injuries and damages to motherboard components.
- In order to avoid damage from static electricity to the motherboard's components, NEVER place your motherboard directly on a carpet. Also remember to use a grounded wrist strap or touch a safety grounded object before you handle the components.
- · Hold components by the edges and do not touch the ICs.
- Whenever you uninstall any components, place them on a grounded anti-static pad or in the bag that comes with the components.
- When placing screws to secure the motherboard to the chassis, please do not overtighten the screws! Doing so may damage the motherboard.


## 2.1 Installing the CPU



- Before you insert the 1718-Pin CPU into the socket, please check if the PnP cap is on the socket, if the CPU surface is unclean, or if there are any bent pins in the socket. Do not force to insert the CPU into the socket if above situation is found. Otherwise, the CPU will be seriously damaged.
- 2. Unplug all power cables before installing the CPU.




Tutorial Video







Δ

Turn your CPU to the correct orientation before opening the CPU socket cover.





Make sure the CPU is aligned with the socket before locking it into place.



Make sure the black cover plate is always in place until it pops off when closing the socket lever.



Please save the cover if the processor is removed. The cover must be placed if you wish to return the motherboard for after service.


## 2.2 Installing the CPU Fan and Heatsink


After you install the CPU into this motherboard, it is necessary to install a larger heatsink and cooling fan to dissipate heat. You also need to spray thermal grease between the CPU and the heatsink to improve heat dissipation. Make sure that the CPU and the heatsink are securely fastened and in good contact with each other.





Please turn off the power or remove the power cord before changing a CPU or heatsink.

## Installing the CPU Cooler (Type 1)













# Installing the CPU Cooler (Type 2)













 ${}^*$ The illustrations shown here are for reference purposes only and may not exactly match the model you purchase.

# Installing the CPU Cooler (Type 3)



























Please note that only one cable should be used at a time in this step.

If you select RGB\_LED1, please install ASRock utility "ASRock Polychrome SYNC".

If you select USB connector, please install AMD utility "SR3 Settings Software".

\*The illustrations shown here are for reference purposes only and may not exactly match the model you purchase.

## 2.3 Installing Memory Modules (DIMM)


This motherboard provides four 288-pin DDR5 (Double Data Rate 5) DIMM slots, and supports Dual Channel Memory Technology.




- For dual channel configuration, you always need to install identical (the same brand, speed, size and chip-type) DDR5 DIMM pairs.
- 2. It is unable to activate Dual Channel Memory Technology with only one or three memory module installed.
- 3. It is not allowed to install a DDR, DDR2, DDR3 or DDR4 memory module into a DDR5 slot; otherwise, this motherboard and DIMM may be damaged.
- 4. The DIMM only fits in one correct orientation. It will cause permanent damage to the motherboard and the DIMM if you force the DIMM into the slot at incorrect orientation.


## **Recommended Memory Configuration**

#### 1 DIMM







## 2.4 Connecting the Front Panel Header









# 2.5 Installing the Motherboard




# 2.6 Installing SATA Drives





# 2.7 Installing a Graphics Card



Skip Step 2 if you install a graphics card into PCIE1 slot. Illustrations here are examples only.

# **Expansion Slots (PCle Slots)**

There are 3 PCI Express slots on the motherboard.




Before installing an expansion card, please make sure that the power supply is switched off or the power cord is unplugged. Please read the documentation of the expansion card and make necessary hardware settings for the card before you start the installation.

#### PCIe slots:


PCIE1 (PCIe 5.0 x16 slot) is used for PCIe x16 lane width graphics cards. PCIE2 (PCIe 3.0 x16 slot) is used for PCIe x4 lane width graphics cards. PCIE3 (PCIe 3.0 x16 slot) is used for PCIe x4 lane width graphics cards.

- $^{\star}$  PCIE1 will run at Gen5x16 with 9000 and 7000 series processors, Gen4x8 with 8000 (Phoenix 1) series processors and Gen4x4 with 8000 (Phoenix 2) series processors.
- \* If M2\_3 is occupied, PCIE2 will downgrade to x2 mode.
- \* If M2\_4 is occupied, PCIE3 will downgrade to x2 mode.


# 2.8 Connecting Peripheral Devices



# 2.9 Connecting the Power Connectors




# 2.10 Power On




# 2.11 Jumpers Setup

The illustration shows how jumpers are setup. When the jumper cap is placed on the pins, the jumper is "Short". If no jumper cap is placed on the pins, the jumper is "Open".



Clear CMOS Jumper (CLRCMOS1) (see p.7, No. 22)

CLRCMOS1 allows you to clear the data in CMOS. The data in CMOS includes system setup information such as system password, date, time, and system setup parameters. To clear and reset the system parameters to default setup, please turn off the computer and unplug the power cord, then use a jumper cap to short the pins on CLRCMOS1 for 3 seconds. Please remember to remove the jumper cap after clearing the CMOS. If you need to clear the CMOS when you just finish updating the BIOS, you must boot up the system first, and then shut it down before you do the clear-CMOS action.



CLRCMOS1
OO
2-pin Jumper
Short: Clear CMOS

Open: Default

#### 2.12 Onboard Headers and Connectors





Onboard headers and connectors are NOT jumpers. Do NOT place jumper caps over these headers and connectors. Placing jumper caps over the headers and connectors will cause permanent damage to the motherboard.

#### System Panel Header

(9-pin PANEL1) (see p.7, No. 18)

Connect the power button, reset button and system status indicator on the chassis to this header according to the pin assignments below. Note the positive and negative pins before connecting the cables.







#### PWRBTN (Power Button):

Connect to the power button on the chassis front panel. You may configure the way to turn off your system using the power button.

#### RESET (Reset Button):

Connect to the reset button on the chassis front panel. Press the reset button to restart the computer if the computer freezes and fails to perform a normal restart.

#### PLED (System Power LED):

Connect to the power status indicator on the chassis front panel. The LED is on when the system is operating. The LED keeps blinking when the system is in S1/S3 sleep state. The LED is off when the system is in S4 sleep state or powered off (S5).


#### HDLED (Hard Drive Activity LED):


Connect to the hard drive activity LED on the chassis front panel. The LED is on when the hard drive is reading or writing data.

The front panel design may differ by chassis. A front panel module mainly consists of power button, reset button, power LED, hard drive activity LED, speaker and etc. When connecting your chassis front panel module to this header, make sure the wire assignments and the pin assignments are matched correctly.

Power LED and Speaker Header (7-pin SPK\_PLED1) (see p.7, No. 19)

Please connect the chassis power LED and the chassis speaker to this header.






Serial ATA3 Connectors

Right Angle:

(SATA3\_1) (see p.7, No. 16)

(SATA3\_2) (see p.7, No. 17)

These two SATA3 connectors support SATA data cables for internal storage devices with up to 6.0 Gb/s data transfer rate.






#### USB 2.0 Headers

(9-pin USB\_7\_8) (see p.7, No. 21)

(9-pin USB\_9\_10) (see p.7, No. 20)

There are two headers on this motherboard. Each USB 2.0 header can support two ports.



#### USB 3.2 Gen1 Headers


#### Right Angle:

(19-pin USB32\_8\_9) (see p.7, No. 15)

#### Vertical:


(19-pin USB32\_10\_11) (see p.7, No. 12)


There are two headers on this motherboard. Each USB 3.2 Gen1 header can support two ports.



Front Panel Type C USB 3.2 Gen2x2 Header (20-pin USB32\_TC2) (see p.7, No. 13)

There is one Front Panel Type C USB 3.2 Gen2x2 Header on this motherboard. This header is used for connecting a USB 3.2 Gen2x2 module for additional USB 3.2 Gen2x2 ports.







Front Panel Audio Header

(9-pin HD\_AUDIO1) (see p.7, No. 28)

This header is for connecting audio devices to the front audio panel.







High Definition Audio supports Jack Sensing, but the panel wire on the chassis must support HDA to function correctly. Please follow the instructions in our manual and chassis manual to install your system.


Chassis Fan Connectors

(4-pin CHA\_FAN1) (see p.7, No. 23)

(4-pin CHA\_FAN2) (see p.7, No. 24)

(4-pin CHA\_FAN3) (see p.7, No. 29)


This header allows you to connect Case or Radiator fan. If you plan to connect a 3-pin fan, please connect it to Pin 1-3.



#### **CPU Fan Connector**

(4-pin CPU\_FAN1) (see p.7, No. 4)

This header allows you to connect CPU fan. If you plan to connect a 3-pin fan, please connect it to Pin 1-3.







#### CPU Fan Connector

(4-pin CPU\_FAN2) (see p.7, No. 5)


This header allows you to connect CPU fan or Water Pump. If you plan to connect a 3-pin fan, please connect it to Pin 1-3.





AIO Pump Fan Connector (4-pin AIO\_PUMP) (see p.7, No. 6)

This header allows you to connect AIO (All-in-One) pump or fan. If you plan to connect a 3-pin AIO cooler fan, please connect it to Pin 1-3.






#### ATX Power Connector

(24-pin ATXPWR1) (see p.7, No. 11)

This motherboard provides a 24-pin ATX power connector. To use a 20-pin ATX power supply, please plug it along Pin 1 and Pin 13.



ATX 12V Power Connectors


(8-pin ATX12V1) (see p.7, No. 1)

(8-pin ATX12V2) (see p.7, No. 2)

This motherboard provides two 8-pin ATX 12V power connectors. To use a 4-pin ATX power supply, please plug it along Pin 1 and Pin 5.

\*Connecting an ATX 12V 8-pin cable to ATX12V2 is optional.


\*Warning: Please make sure that the power cable connected is for the CPU and not the graphics card. Do not plug the PCIe power cable to this connector.




#### PI TPM Header

(13-pin SPI\_TPM\_J1) (see p.7, No. 14)

This connector supports SPI Trusted Platform Module (TPM) system, which can securely store keys, digital certificates, passwords, and data. A TPM system also helps enhance network security, protects digital identities, and ensures platform integrity.






#### Thermistor Cable Header


(2-pin T\_SENSOR1) (see p.7, No. 27)

The Thermistor Cable Header is used to connect a thermistor cable to monitor the temperature of the critical component. Plug the thermistor cable that comes with the package to the header, and then attach the sensor end to the component to detect the temperature.





Connect your Thermistor Cable to the **Thermistor Cable Header** (T\_SENSOR1) on the motherboard.




#### RGB LED Header

(4-pin RGB\_LED1) (see p.7, No. 26)


This RGB header is used to connect RGB LED extension cable which allow users to choose from various LED lighting effects.

Caution: Never install the RGB LED cable in the wrong orientation; otherwise, the cable may be damaged.





Connect your RGB LED strip to the RGB LED Header (RGB\_LED1) on the mother-board.





- Never install the RGB LED cable in the wrong orientation; otherwise, the cable may be damaged.
- Before installing or removing your RGB LED cable, please power off your system and unplug the power cord from the power supply. Failure to do so may cause damages to motherboard components.



- 1. Please note that the RGB LED strips do not come with the package.
- The RGB LED header supports standard 5050 RGB LED strip (12V/G/R/B), with a maximum power rating of 3A (12V) and length within 2 meters.

Addressable LED Headers


(3-pin ADDR\_LED1) (see p.7, No. 25)

(3-pin ADDR\_LED2) (see p.7, No. 10)


(3-pin ADDR\_LED3) (see p.7, No. 9)

These headers are used to connect Addressable LED extension cables which allow users to choose from various LED lighting effects.

Caution: Never install the Addressable LED cable in the wrong orientation; otherwise, the cable may be damaged.



Connect your Addressable RGB LED strips to the Addressable LED Headers (ADDR\_LED1 / ADDR\_LED3) on the motherboard.





- Never install the Addressable LED cable in the wrong orientation; otherwise, the cable may be damaged.
- Before installing or removing your Addressable LED cable, please power off your system and unplug the power cord from the power supply. Failure to do so may cause damages to motherboard components.




- 1. Please note that the Addressable LED strips do not come with the package.
- The Addressable LED header supports WS2812B addressable RGB LED strip (5V/ Data/GND), with a maximum power rating of 3A (5V) and length within 2 meters.


# 2.13 Smart Button

The motherboard has one smart button: BIOS Flashback Button, allowing users to flash the BIOS.

BIOS Flashback Button (BIOS\_FB1) (see p.9, No. 15)

BIOS Flashback Button allows users to flash the BIOS.





ASRock BIOS Flashback feature allows you to update BIOS without powering on the system, even without CPU.



Before using the BIOS Flashback function, please suspend BitLocker and any encryption or security relying on the TPM. Make sure that you have already stored and backup-ed the recovery key. If the recovery key is missing while encryption is active, the data will stay encrypted and the system will not boot into the operating system. It is recommended to disable fTPM before updating the BIOS. Otherwise an unpredictable failure may occur.


To use the USB BIOS Flashback function, Please follow the steps below.

- 1. Download the latest BIOS file from ASRock's website: http://www.asrock.com.
- Copy the BIOS file to your USB flash drive. Please make sure the file system of your USB flash drive must be FAT32.
- 3. Extract BIOS file from the zip file.
- 4. Rename the file to "creative.rom" and save it to the root directory of X: USB flash drive.
- Plug the 24 pin power connector to the motherboard. Then turn on the power supply's AC switch.
  - \*There is no need to power on the system.
- 6. Then plug your USB drive to the USB BIOS Flashback port.
- 7. Press the BIOS Flashback Switch for about three seconds. Then the LED starts to blink.
- 8. Wait until the LED stops blinking, indicating that BIOS flashing has been completed.
  \*If the LED light turns solid green, this means that the BIOS Flashback is not operating properly. Please make sure that you plug the USB drive to the USB BIOS Flashback port.
  - \*\*If the LED does not light up at all then please disconnect power from the system and remove/disconnect the CMOS battery from the motherboard for several minutes. Reconnect power and battery and try again.

# 2.14 Post Status Checker

Post Status Checker (PSC) diagnoses the computer when users power on the machine. The LEDs light up to show what component is running into an issue. They emit red, yellow, white and yellow-green lights to indicate, respectively, the CPU, memory, VGA and storage are not detected or fail. They will remain lit until the issue is fixed. The lights go off if the four mentioned above are functioning normally.

Component	LED Indicator	Status
CPU	Solid Red	indicates CPU is dysfunctional.
DRAM	Solid Yellow	indicates DRAM is dysfunctional.
VGA	Solid White	indicates GPU is dysfunctional.
BOOT	Solid Yellow-Green	indicates boot device is dysfunctional.





It is normal for the DRAM status LED to blink during memory training. This indicates the system is working properly.




Tutorial Video

# 2.15 M.2 SSD Installation Guide (M2\_1)

The M.2 is a small size and versatile card edge connector that aims to replace mPCIe and mSATA. The Blazing M.2 Socket (M2\_1, Key M) supports type 2280 PCIe Gen5x4 (128 Gb/s) mode.


- \* M2\_1 is the first priority for M.2 installation.
- \* M2\_1 will run at Gen5x4 with 9000 and 7000 series processors and Gen4x4 with 8000 (Phoenix 1 and Phoenix 2) series processors.

# Installing the M.2 SSD



#### Step 1


Prepare a M.2 SSD.



# No. 1 Nut Location A PCB Length 8cm Module Type Type2280

#### Step 2


Depending on the PCB type and length of your M.2 SSD, find the corresponding nut location to be used.



#### Step 3


Push the button on the M.2 heatsink in the direction shown (A). Then lift up the heatsink (B) and move it in the direction shown (C).

\*Please remove the protective films on the bottom side of the M.2 heatsink before you install a M.2 SSD.




#### Step 4

Align and gently insert the M.2 SSD into the M.2 slot. Please be aware that the M.2 SSD only fits in one orientation.




## Step 5

Ensure that the notch at the end of the M.2 SSD aligns with the nut. Then secure the M.2 SSD by turning the nut lock clockwise to its locked position.



#### Step 6


Hook the tab of the M.2 heatsink back onto the standoff.



#### Step 7

Press the M.2 heatsink down into place.

\*Be sure not to press down the button on the M.2 heatsink.



## Step 8

Complete.

For the latest updates of M.2 SSD support list, please visit our website for details:  $\underline{\text{http://}}$  www.asrock.com


# 2.16 M.2 SSD Installation Guide (M2\_2)

The M.2 is a small size and versatile card edge connector that aims to replace mPCIe and mSATA. The Blazing M.2 Socket (M2\_2, Key M) supports type 2280 PCIe Gen5x4 (128 Gb/s) mode.

\*M2\_2 will run at Gen5x4 with 9000 and 7000 series processors and Gen4x4 with 8000 (Phoenix 1) series processors. M2\_2 will be unavailable with 8000 (Phoenix 2) series processors.


\*If M2\_2 is occupied, both rear USB4 Type-C Ports and M2\_2 will downgrade to x2 mode. You can switch M2\_2 to x4 mode in BIOS setting, but doing so will disable USB4\_TC1 and USB4\_TC2.

# Installing the M.2 SSD




#### Step 1


Prepare a M.2 SSD.



#### Step 2

Depending on the PCB type and length of your M.2 SSD, find the corresponding nut location to be used.






#### Step 3


Before installing a M.2 SSD, please loosen the screws to remove the M.2 heatsink.

\*Please remove the protective films on the bottom side of the M.2 heatsink before you install a M.2 SSD.



#### Step 4


Align and gently insert the M.2 SSD into the M.2 slot. Please be aware that the M.2 SSD only fits in one orientation.



#### Step 5

Ensure that the notch at the end of the M.2 SSD aligns with the nut.

Then secure the M.2 SSD by turning the nut lock clockwise to its locked position.



# Step 6

Tighten the screws with a screwdriver to secure the M.2 heatsink into place. Please do not overtighten the screw as this might damage the M.2 SSD and M.2 heatsink.


For the latest updates of M.2 SSD support list, please visit our website for details: <a href="http://www.asrock.com">http://www.asrock.com</a>

# 2.17 M.2 SSD Installation Guide (M2\_3)

The M.2 is a small size and versatile card edge connector that aims to replace mPCIe and mSATA. The Hyper M.2 Socket (M2 $_3$ , Key M) supports type 2280 PCIe Gen4x4 (64 Gb/s) mode.


\*If M2\_3 is occupied, PCIE2 will downgrade to x2 mode.

# Installing the M.2 SSD



#### Step 1


Prepare a M.2 SSD.



## Step 2

Depending on the PCB type and length of your M.2 SSD, find the corresponding nut location to be used.


No.	1
Nut Location	A
PCB Length	8cm
Module Type	Type2280



## Step 3


Before installing a M.2 SSD, please loosen the screws to remove the M.2 heatsink.

\*Please remove the protective films on the bottom side of the M.2 heatsink before you install a M.2 SSD.




#### Step 4

Align and gently insert the M.2 SSD into the M.2 slot. Please be aware that the M.2 SSD only fits in one orientation.



#### Step 5

Ensure that the notch at the end of the M.2 SSD aligns with the nut. Then secure the M.2 SSD by turning the nut lock clockwise to its locked position.



#### Step 6


Tighten the screws with a screwdriver to secure the M.2 heatsink into place. Please do not overtighten the screw as this might damage the M.2 SSD and M.2 heatsink.

For the latest updates of M.2 SSD support list, please visit our website for details:  $\underline{\text{http://}}$  www.asrock.com

# 2.18 M.2 SSD Installation Guide (M2\_4)


The M.2 is a small size and versatile card edge connector that aims to replace mPCIe and mSATA. The Hyper M.2 Socket (M2 $_4$ , Key M) supports type 2230/2242/2260/2280 PCIe Gen4x4 (64 Gb/s) mode.

# Installing the M.2 SSD



#### Step 1

Prepare a M.2 SSD.




#### Step 2

Depending on the PCB type and length of your M.2 SSD, find the corresponding nut location to be used.

No.	1	2	3	4
Nut Location	A	В	С	D
PCB Length	3cm	4.2cm	6cm	8cm
Module Type	Type 2230	Type 2242	Type 2260	Type 2280


<sup>\*</sup> If M2\_4 is occupied, PCIE3 will downgrade to x2 mode.



#### Step 3

Before installing a M.2 SSD, please loosen the screws to remove the M.2 heatsink.


\*Please remove the protective films on the bottom side of the M.2 heatsink before you install a M.2 SSD.



#### Step 4

Use a screwdriver to remove the standoff.


Skip Step 4 if your M.2 SSD is Type 2280.



#### Step 5


Peel off the yellow protective film on the nut to be used. Tighten the standoff into the desired nut location on the motherboard with a screwdriver.

Skip Step 5 if your M.2 SSD is Type 2280.




#### Step 6

Align and gently insert the M.2 SSD into the M.2 slot. Please be aware that the M.2 SSD only fits in one orientation.



#### Step 7

Ensure that the notch at the end of the M.2 SSD aligns with the nut. Then secure the M.2 SSD by turning the nut lock clockwise to its locked position.



#### Step 8

Tighten the screws with a screwdriver to secure the M.2 heatsink into place. Please do not overtighten the screw as this might damage the M.2 SSD and M.2 heatsink.

Version 1.0
Published July 2025
Copyright©2025 ASRock INC. All rights reserved.

# **Copyright Notice**

No part of this documentation may be reproduced, transcribed, transmitted, or translated in any language, in any form or by any means, except duplication of documentation by the purchaser for backup purpose, without written consent of ASRock Inc.

Products and corporate names appearing in this documentation may or may not be registered trademarks or copyrights of their respective companies, and are used only for identification or explanation and to the owners' benefit, without intent to infringe.

#### Disclaimer

Specifications and information contained in this documentation are furnished for informational use only and subject to change without notice, and should not be constructed as a commitment by ASRock. ASRock assumes no responsibility for any errors or omissions that may appear in this documentation.

To the extent permitted by law, with respect to the contents of this documentation, ASRock does not provide warranty of any kind, either expressed or implied, including but not limited to the implied warranties or conditions of merchantability or fitness for a particular purpose. In no event shall ASRock, its directors, officers, employees, or agents be liable for any indirect, special, incidental, or consequential damages (including damages for loss of profits, loss of business, loss of data, interruption of business and the like), even if ASRock has been advised of the possibility of such damages arising from any defect or error in the documentation or product.

#### **FCC Compliance Statement**



This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

# **AWARNING**

- INGESTION HAZARD: This product contains a button cell or coin battery.
- **DEATH** or serious injury can occur if ingested.
- A swallowed button cell or coin battery can cause **Internal Chemical Burns** in as little as **2 hours**.
- KEEP new and used batteries OUT OF REACH of CHILDREN
- Seek immediate medical attention if a battery is suspected to be swallowed or inserted inside any part of the body.



- Remove and immediately recycle or dispose of used batteries according to local regulations and keep away from children. Do NOT dispose of batteries in household trash or incinerate.
- Even used batteries may cause severe injury or death.
- Call a local poison control center for treatment information.
- Battery type: CR2032
- Battery voltage: 3V
- Non-rechargeable batteries are not to be recharged.
- Do not force discharge, recharge, disassemble, heat above (manufacturer's specified temperature rating) or incinerate. Doing so may result in injury due to venting, leakage or explosion resulting in chemical burns.
- This product contains an irreplaceable battery.
- This icon indicates that a swallowed button battery can cause serious injury or death. Please keep batteries out of sight or reach of children.

#### **CALIFORNIA, USA ONLY**

The Lithium battery adopted on this motherboard contains Perchlorate, a toxic substance controlled in Perchlorate Best Management Practices (BMP) regulations passed by the California Legislature. When you discard the Lithium battery in California, USA, please follow the related regulations in advance.

"Perchlorate Material-special handling may apply, see <a href="www.dtsc.ca.gov/hazardouswaste/perchlorate">www.dtsc.ca.gov/hazardouswaste/perchlorate</a>"

#### **CALIFORNIA, USA ONLY**



**WARNING:** Risk of cancer and reproductive harm from exposure to Lead. See <a href="https://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a>

# **CE Conformity**



ASRock INC. hereby declares that this device is in compliance with the essential requirements and other relevant provisions of related Directives. Full text of EU declaration of conformity is available at: http://www.asrock.com

ASRock follows the green design concept to design and manufacture our products, and makes sure that each stage of the product life cycle of ASRock product is in line with global environmental regulations. In addition, ASRock disclose the relevant information based on regulation requirements.

Please refer to <a href="https://www.asrock.com/general/about.asp?cat=Responsibility">https://www.asrock.com/general/about.asp?cat=Responsibility</a> for information disclosure based on regulation requirements ASRock is complied with.

# **UKCA Conformity**



ASRock INC. hereby declares that this device is in compliance with the essential requirements and other relevant provisions of related UKCA Directives. Full text of UKCA declaration of conformity is available at: http://www.asrock.com

#### **Consumer Limited Warranty - Australia**

Our goods come with guarantees that cannot be excluded under the Australian Consumer Law. You are entitled to a replacement or refund for a major failure and compensation for any other reasonably foreseeable loss or damage caused by our goods. You are also entitled to have the goods repaired or replaced if the goods fail to be of acceptable quality and the failure does not amount to a major failure. If you require assistance please call ASRock Tel: +886-2-28965588 ext.123 (Standard International call charges apply)



#### WARNING

THIS PRODUCT CONTAINS A BUTTON BATTERY If swallowed, a button battery can cause serious injury or death. Please keep batteries out of sight or reach of children.

#### **Proper Disposal**



DO NOT throw the motherboard in municipal waste. This product has been designed to enable proper reuse of parts and recycling. This symbol of the crossed out wheeled bin indicates that the product (electrical and electronic equipment) should not be placed in municipal waste. Check local regulations for disposal of electronic products.

#### Class B ITE

この装置は、クラスB情報技術装置です。この装置は、家庭環境で使用することを目的としていますが、この装置がラジオやテレビジョン受信機に近接して使用されると、受信障害を引き起こすことがあります。取扱説明書に従って正しい取り扱いをして下さい。

#### Trademark Information

The terms HDMI\* and HDMI High-Definition Multimedia Interface, and the HDMI logo are trademarks or registered trademarks of HDMI Licensing LLC in the United States and other countries.



# European Community Radio Equipment Directive Compliance Statement

This device complies with directive 2014/53/EU issued by the Commision of the European Community. This equipment complies with EU radiation exposure limits set forth for an uncontrolled environment.

This equipment should be installed and operated with minimum distance 20cm between the radiator & your body.

Operations in the 5.15-5.35/6GHz band are restricted to indoor usage only.





#### **Radio Frequency Bands and Maximum Power Levels**

- Features: Wi-Fi 6E, BT, Wi-Fi 7
- Frequency Range: 2.4 GHz: 2400-2485MHz; 5 GHz: 5150-5350MHz, 5470-5725MHz, 5725-5850MHz; 6 GHz: 5955-6415MHz
- Max Power Level: 2.4 GHz: 20dBm; 5 GHz: 23dBm; 6 GHz: 23dBm

# Compliance Statement of Innovation, Science and Economic Development Canada (ISED)

This device complies with with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device. Operation in the band 5150-5250 MHz is only for indoor use to reduce the potential for harmful interference to co-channel mobile satellite systems. CAN ICES-003(B)/NMB-003(B)

# NCC 無線設備警告聲明

經型式認證合格之低功率射頻電機,非經許可,公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。 低功率射頻電機之使用不得影響飛航安全及干擾合法通信; 經發現有干擾現象時,應立即停用,並改善至無干擾時方得繼續使用。前項合法通信,指依電信法規定作業之無線電通信。低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

**ASRock Incorporation** 

Contains Wi-Fi 7 module with Bluetooth

#### Azurewave WiFi 7 AW-EB601NF

Model: RTL8922AE

<u></u>
<u>RN7</u>

FCC ID: TX2-RTL8922AE

IC:6317A-RTL8922AE







5.9~6.4GHz indoor use only

# BSMI 限用物質及元素清單

單元	限用物質及其化學符號						
	鉛 (Pb)	鎘 (Cd)	汞 (Hg)	六價鉻 (Cr <sup>+6</sup> )	多溴聯苯 (PBB)	多溴聯苯醚 (PBDE)	
電路板	0	0	0 0 0		0	0	
電子元件	-	0	0	0	0	0	
線材	-	0	0	0 0		0	
配件	-	0	0	0	0	0	

備考 1. 〝超出 0.1 wt %″ 及 〝超出 0.01 wt %″ 係指限用物質之百分比含量超出百分比含量基準值

備考 2. \*○ 《 係指該項限用物質之百分比含量未超出百分比含量基準值。

備考 3. "一" 係指該項限用物質為排除項目。

#### China RoHS

## 电子信息产品污染控制标示

依据中国发布的「电子电气产品中限用物质的限量要求」及 SJ/T 11364-2024《电器电子产品有害物质限制使用标识要求》,电子信息产品应进行标示,藉以向消费者揭露产品中含有的有毒有害物质或元素不致发生外泄或突变从而对环境造成污染或对人身、财产造成 严重损害的期限。依上述规定,您可于本产品之印刷电路板上看见图一之标示。图一中之数字为产品之环保使用期限。由此可知此主板之环保使用期限为10年。



图—

## 产品中有害物质的名称及含有信息表

部件名称	有害物质或元素									
HILL HAV	铅 (Pb)	镉 (Cd)	汞 (Hg)	六价铬 (Cr(VI))	多溴联苯 (PBB)	多溴二苯 醚 (PBDE)	邻苯二甲酸二 (2-乙基)己酯 (DEHP)	邻苯二甲酸丁基苄酯 (BBP)	邻苯二甲酸二正丁酯 (DBP)	邻苯二甲酸二异丁酯 (DIBP)
印刷电路板 及电子组件	Х	0	0	0	0	0	0	0	0	0
外部信号连 接头及线材	х	0	0	0	0	0	0	0	0	0

- 以上表格依据 SI/T 11364-2024 的规定编制。
- 注 1: O: 表示该有害物质在该部件所有均质材料中的含量均满足电器电子产品有害物质限制使用国家标准要求。 X: 表示该有害物质至少在该部件的某一均质材料中的含量不满足电器电子产品有害物质限制使用国家标准 要求。
- 注 2: 以上未列出的部件,表明其有害物质含量均满足电器电子产品有害物质限制使用国家标准要求。
- 备注: 此产品所标示之环保使用年限,系指在一般正常使用状况下。