











### Hellhound AMD Radeon™ RX 6600 XT 8GB GDDR6

#### **SPECIFICATION**

EAN CODE	4713436173502	Bus Standard	PCIE 4.0
Graphics Engine	AXRX 6600XT 8GBD6-3DHL/OC	Display Connectors	1 x HDMI 2.1 , 3 x DisplayPort 1.4
Video Memory	8GB GDDR6	Form Factor	ATX
Stream Processor	2048 Units	Cooler	2.2 Slot Dual Fan
		Power Connector	One 8-pin PCI Express Power Connector
Engine Clock	Game 2382MHz(OC)/2359MHz(Silent)	OpenGL	4.6
	Boost 2593MHz(OC)/2589MHz(Silent)	DirectX® Support	12
Memory Clock	16.0 Gbps	Minimum System Power	500W
Memory Interface	128-bits	Card Dimension(mm)	220*132*45mm
Accessories Rundle	PowerColor Installation Guide Card		

Accessories Bundle PowerColor Installation Guide Card

#### **FEATURES**



### Two Ball Bearing - 4X greater longevity

The cooling fan utilizes two-ball bearing technology, increasing the longevity of the fans by up to 4 times.



### **LED Light**

The LED lighting on the shroud and backplate makes your system more stylish and chiller.



## Exclusive New Cooling-Fan Design, Advanced Cooling Solution

Compared with previous generation, PowerColor Graphics Card uses an exclusive new cooling-fan design to increase airflow and air pressure by up to 60%.



# Mute Fan Technology - 0db - Silent gaming

Mute Fan Technology intelligently turns off the fan below 60°C , providing silent gaming during medium and low-load while reducing power consumption.



#### **Copper Base Direct Touch**

A smooth copper base directly contacts the GPU to enhance exceptional heat dissipation efficiency.



#### **Dual BIOS**

Choosing the BIOS that fits your need: better overclocking or silent operation.

The entire information provided herein are for reference only. PowerColor reserves the right to modify or revise the content at anytime without prior notice.

<sup>\* &#</sup>x27;Game Clock' is the expected GPU clock when running typical gaming applications, set to typical TGP (Total Graphics Power). Actual individual game clock results may vary.

\* 'Boost Clock' is the maximum frequency achievable on the GPU running a burstyworkload. Boost clock achievability, frequency, and sustainability will vary based on several factors, including but not limited to:thermal conditions and variation in applications and workloads.