

LENOVO™ SMARTCARD WIRED KEYBOARD II



SECURITY AT YOUR FINGERTIPS.

In workplaces where information is sensitive, authentication and access control are the keys to preventing data disasters. Our latest Lenovo Smartcard Wired Keyboard II is a purpose-built solution that gives you the best of both worlds. The power of a full-size keyboard with the added security of an integrated Smartcard reader for applications that require enhanced protection.

WHY YOU NEED LENOVO SMARTCARD WIRED KEYBOARD II



Innovate Smartcard Technology

Keep your business private with the latest Smartcard technology. Prevent unauthorized access to your computers and networks. Streamline your workflow and reduce costs. Plus, enjoy the flexibility to use a variety of sizes, protocols, and Standard Application Interfaces (API).



Capable Full-Size Formfactor

Stay comfortable and productive with a full-size keyboard that's as it should be. Responsive. Low profile. Quiet. And fully functional with Fn-hotkeys for shortcut access.



Business-Ready Design

Engineered to last and not get in the way. The Smartcard reader features an ergonomic 30° insertion angle and is good for up to 100,000 swipes. With keys good for 10 million clicks, you can rest knowing you'll be ready when duty calls.

LENOVO™ SMARTCARD WIRED KEYBOARD II



SPECIFICATIONS

PERFORMANCE & DESIGN

Layout

Full-size 3-zone

Number of Keys

Varies depending on language

Hotkeys

Dedicated Fn Hotkeys

Spill-Resistant

No

Tilt Adjustable

Yes, 3° or 8°

Color

Black

LED Indicator

Fn Lock, Caps Lock, Num Lock, Scroll Lock, Smartcard Reader LED

Keycaps

Low-profile Design

Switch Life

Up to 10 Million Clicks

Acoustics

Up to 50 dB

Dimensions (W x D x H)

(mm) : 445 x 162 x 24

(inches) : 17.52" x 6.37" x 0.94"

Weight

Starting at 0.79 kg (1.74 lbs)

Connectivity

Interface : Wired via USB

Cable Length : 2.0 m

SMARTCARD FUNCTION

Support

All ISO 7816 Smart Cards

Interface

Reads from and writes to all ISO 7816-1, 2, 3, 4 cards, Class A and AB cards and microprocessor smart cards (T=0, T=1, S=8, S=9, S=10)

Chipset

Identiv uTrust 2190F

Power

USB Port, 100 mA maximum draw

Supports 3V and 5V cards

Dustproof

Yes

Lifecycle

Up to 100,000 cycles

Other Information

Support for Secure PIN Entry Mode (Class 2 terminal)

Support for 3V and 5V Smartcards

Support for Standard Applications Interfaces (API)

Support for EMV*

Support for FIPS-201 compliant

INFORMATION

Supported OS

Windows 11, Windows 10, Windows 7

PC Systems

Supported PC with USB-A 2.0 Port or Higher

Certifications

CB, cTUVus, TUV Mark, CE EMC, BIS, FCC, VCCI, BSMI, KCC

Warranty

3 Years

Ship Group (What's in the box)

Lenovo Smartcard Wired Keyboard II Documents

PN (Available layout)

4Y41B69353 : US English

4Y41B69354 : Greek/US English

4Y41B69355 : Russian/Cyrillic

4Y41B69356 : Thai

4Y41B69357 : US English with Euro Symbol

4Y41B69358 : Hebrew

4Y41B69360 : LA Spanish

4Y41B69361 : Arabic

4Y41B69362 : Arabic/French

4Y41B69363 : Belgium/French

4Y41B69364 : Belgium/UK

4Y41B69365 : Bulgarian

4Y41B69366 : Croatian/Slovenian (234)

4Y41B69367 : Czech

4Y41B69368 : Danish

4Y41B69369 : French

4Y41B69370 : Serbian Cyrillic (118)

4Y41B69371 : French Canadian (058)

4Y41B69372 : German

4Y41B69373 : Greek

4Y41B69374 : Hungarian

4Y41B69375 : Turkish 440 F-type

4Y41B69376 : Italy

4Y41B69377 : Norwegian

4Y41B69378 : Portuguese

4Y41B69379 : Slovak

4Y41B69380 : Spanish

4Y41B69381 : Swedish/Finnish

4Y41B69382 : Swiss French/German

4Y41B69383 : Turkish Q-type

4Y41B69384 : UK English

4Y41B69385 : Japanese

4Y41B69386 : Korean

4Y41B69387 : Brazil/Portuguese

4Y41B69388 : Czech/Slovak

4Y41B69389 : Icelandic

4Y41B69390 : Nordic

* Lenovo Smartcard Keyboard support with EMV but no certification, because the EMV certification is no longer required for the smart card reader.



[ACCESSORYSMARTFIND.LENOVO.COM](https://www.lenovo.com/accessorysmartfind)

Lenovo reserves the right to alter product offerings and specifications at any time, without notice. Lenovo makes every effort to ensure accuracy of all information but is not liable or responsible for any editorial, photographic, or typographic errors. All images are for illustration purposes only. For full Lenovo product, service, and warranty specifications, visit www.lenovo.com. Lenovo makes no representations or warranties regarding third-party products or services. **Trademarks:** The following are trademarks or registered trademarks of Lenovo: Lenovo, the Lenovo logo, Rescue and Recovery, ThinkPad, ThinkCentre, ThinkStation, ThinkServer, ThinkVantage, and ThinkVision. Other company, product, and service names may be trademarks or service marks of others. Battery life (and recharge times) will vary based on many factors, including system settings and usage. Visit www.lenovo.com/lenovo/us/en/safecomp/ periodically for the latest information on safe and effective computing. ©2021 Lenovo. All rights reserved.

Lenovo™